



DS2400

duct, pipe, conduit, wall masker for SCIF / secure rooms

The industry's largest supplier of design-build soundmasking solutions

tech spec_sheet

Features:

- Fills pipes, square ducts and round ducts, and walls with soundmasking
- Lightweight and easy to install
- Does not cause pressure drop or alter air flow when applied to ductwork
- Does not require separate transformer
- Individual level adjustment
- Durable plenum-rated metal housing



Description:

The Dynasound DS2400 pipe, duct, and wall Soundmasker is used to protect pipes, ducts, and walls against human and electronic eavesdropping by filling them with full bandwidth soundmasking. The unit may be attached to the exterior of any pipe or duct, whether square or round. It may also be attached to the vertical surface of any partition wall. The DS2400 is critical to the securing of pipes and ducts when DIAM and DCID requirements for SCIF need to be met. The DS2400 Soundmasker may be used to ensure eavesdropping protection of pipes and ducts that breach the perimeter of a secure environment by resonating these penetrations, filling them with soundmasking and/or misinformation. Additionally, it resonates the plane of any wall along the perimeter of a secure environment. When controlled by Dynasound's DS102 Series security generators and amplifiers, it also protects against sophisticated signal recovery techniques.

Specifications:

Driver:	non-conventional security type
Transformer:	Primary 70.7v, Secondary 8 Ohms, Switch Positions: 1/8, 1/4, 1/2, 1, 2, 4 watts
Dimensions:	5 inches x 5 inches x 1 3/4 inches
Finish:	black
Weight:	2 lbs.

Architect's Specification:

Sound masking assembly shall be Dynasound model DS2400. Unit shall contain a acoustical driver, equipped with a 70.7V transformer, and be designed for peel-and-stick installation on to ducts, pipes, conduits and wall surfaces. The unit shall be factory assembled, wired and ready for installation. The unit shall include an external tap selector switch with an off position and 1/8, 1/4, 1/2, 1, 2 and 4 watt power taps. Strain relief for the speaker leads shall be provided. The enclosure shall measure 5 inches by 5 inches by 1 3/4 inches tall. Similar devices requiring external transformers are not acceptable. Devices not designed for use on 70.7 volt systems are not acceptable.

Use with:



DS1042 system



DS1092 system



DS1625 amplifier



DS1628 amplifier